


**Use this section to keep your
important information!**



REMINDER

mySPYPOINT account
Email: _____
Password: _____

Rogers account
Phone number: _____
Password: _____
PIN code: _____

How to activate your *SPYPOINT LIVE* camera

Note: If you have any problems during the activation of your camera, make sure you have already read and followed each step in this procedure before contacting Spypoint's technical support. This way, you will be able to provide the necessary information to the technician for them to accurately provide proper support.

This procedure will guide you through the process of activating your new camera. It is important to carefully follow each of the following steps:

- 1. Create your *mySPYPOINT* account**
- 2. Activate and add a data plan to your Rogers SIM card.**

Note: If you use your own SIM card on which a "Data" plan is already activated, steps 2 is not required. Please note that only GSM/GPRS service providers as Rogers or FIDO are compatible with the *SPYPOINT LIVE* camera in Canada. Other 3G network service providers may not support GSM/GPRS network, please verify with your service provider before buying a SIM card.

Before beginning:

- Get an unactivated SIM card from a Rogers authorized dealer.
- It is important to use ***Internet Explorer*** (Safari for Mac users) during this entire procedure. Mozilla Firefox or other web browsers are not compatible.
- Prepare the following requirements:
 - ***SPYPOINT LIVE*** camera
 - SIM card (Rogers unactivated SIM card or your own SIM card on which a "Data" plan is already activated)
 - 8 AA batteries or a ***SPYPOINT LIT-09*** lithium battery pack
 - Credit card
 - Pencil
 - Computer with internet access
 - Phillips screwdriver

1 **Creating your *mySPYPOINT* account**

These steps will allow you to use the interface of the website "*mySPYPOINT*" to save and manage photos received from your *SPYPOINT LIVE* camera during one year. Fees of \$ 19.99+TX./yr per camera are required in order to use this service.

1. To begin registration of your new "*mySPYPOINT*" account , go to www.myspypoint.com
2. Click "REGISTER NOW" and enter your personal information as indicated, then click "Subscribe" (this may take few seconds)

3. You will be asked to confirm your registration via email. An email from "info@mispypoint.com" will be automatically sent to your personal email, the one you entered in #2.
4. Once confirmed, a new page will open and you will have access to your new account.
5. From this new "*mySPYPOINT*" website page, click "Account".
6. Click "Add" in the upper right hand corner of the page to link your *SPYPOINT LIVE* camera to your account.
7. Enter a name for your camera. For example, if your camera is installed at your chalet, you can call it "COTTAGE".
8. Insert your SIM card into the *SPYPOINT LIVE* camera. The SIM card compartment is located under the batteries. You need to use a Phillips screwdriver to open and close the compartment. (see section "Installing the SIM card" of the user manual for more details)
9. Turn on your camera and choose TEST mode.
10. Back to the registration form, enter the SIM card number that appears on the screen of your camera in TEST mode.
11. Enter the serial number of your camera (displayed at the bottom left corner of the camera screen in the main menu) and click "Continue". If you do not see a serial number on the screen, make sure your camera has the latest software update available at www.spypoint.com
12. Select the monthly data transfer limit according to your service provider data plan. **This option makes sure you do not exceed the amount of data permitted on your data plan.** An email will be sent to the address related to your account when you have reached 80% of your monthly limit. The picture transmission to your *mySPYPOINT* account will be automatically blocked if the amount of data transfer reaches 95% of the limit chosen (the camera continues recording locally on the SD card). This monthly data transfer limit can be changed at a later time through the cameras management section of your account under the "Account" tab.
13. An invoice will appear to pay your registration. This will give you access to your *mySPYPOINT* account linked with your *SPYPOINT LIVE* camera for one year. Enter your credit card information as requested.
14. Check the box "I have read and I accept the methods of transaction." and click "Pay".
15. If you are using your own SIM card on which a "Data" plan is already activated, you are now ready to use your camera. If you are using a Rogers unactivated SIM card, go to the next section to add a data plan and refill your card.

2. Purchasing and adding a data plan to your Rogers account.

16. Go to www.rogers.com
17. Roll over "WIRELESS" button and click "Pay As You Go".
18. Click on "ACTIVATE NOW".
19. In the field "Serial Number", enter this number : **357413000379705**
20. In the field "SIM Number", Enter the 20 digits of your Rogers SIM card. This card must be brand new and have never been used in another cellular device before.
21. Choose your province and the city closest to your city of residence in the appropriate fields.
22. Click "Continue"
23. One in the section "2. Plan Selection", check the box corresponding to "By the Minute - Anytime".
24. Click "Continue".
25. One in the section "3. Add Ons Selection", click the "Data add-ons" tab on the right side of the page.

26. Click "add" next to the option of your choice: "\$10/month for 100MB Data Add-on" OR "\$25/month for 500MB Data Add-on"

Approximate comparison between data plans to help you choose your Rogers data plan:

100 MB = 5 000 thumbnails OR 1 000 high resolution pictures = \$ 10.00 / month
500 MB = 25 000 thumbnails OR 5 000 high resolution pictures = \$ 25.00 / month

27. Click "Add to Cart".
28. Click "Proceed to Cart Summary".
29. Click "Proceed to Checkout".
30. On the billing page, select "Credit Card" as "Payment Methods".
31. Enter the amount you want to refill in the field "Top-up Amount". For example, if you previously selected a data plan of \$ 10.00, enter the number 10.00 in this field.

IMPORTANT: Your ROGERS account works like a bank account into which you place money. Withdrawals are made each month to cover expenses related to the "Data" option that you chose previously (100Mo/month or 500Mo/month for sending photos via mysypoint). Mandatory fee for access to 911 emergency services are also withdrew each month (about \$ 1.15 / month, depending on your province of residence). For this reason, it is necessary that the balance on your account always includes the amount of your "Data" option as well as the fee for access to emergency services. When opening your account, we suggest adding \$ 20 extra, which will cover the fee for access to emergency services for the upcoming months.

32. Then, fill out the rest of the required fields: credit card number, name, home address, etc..
33. Click "Continue".
34. On the page "2. Number Configuration", click "Get a New Number".
35. Fill in the fields Province, City of residence and Area Code and click "Search for Available Numbers". (These fields might be automatically filled.)
36. Select the number of your choice from the list and write it down in the "Reminder" section located at the first page of this procedure.
37. Click "Get Number".
38. On the page "ORDER SUMMARY", check the box "I Accept" at the bottom of the page and click "Submit Order".
39. You will receive an email from Rogers confirming the activation of your account. You will find a summary of your account information such as your personal identification number (PIN). This number is only required if you want to refill your account by phone or using a prepaid card.
40. Turn on your **SPYPOINT LIVE** camera.
41. Go to the SETTINGS menu and change the option "Carrier" to Rogers.
42. Go back to main menu and choose TEST mode. Make sure that the signal strength icon on the upper left corner of the screen shows at least 1 white bar. If you see a message on the screen indicating your SIM card number, press OK to make it disappear.
43. Stay in TEST mode, you will see a message from Rogers confirming your phone number (this process may take up to 5 minutes). Delete this message by pressing OK. It is possible that you get the error message "Could not connect". If this happens, it may be necessary to return to the main menu by pressing the BACK button and to go back to TEST mode. It is possible that you receive other messages from Rogers, press OK to delete them.
44. You will now be ready to use your **SPYPOINT LIVE** camera.

45. To verify the configuration, set the camera to TEST mode. After a few seconds, if the cellular signal strength icon at the top of the screen is white (not red) and the message "Connection successful" appears, your camera is ready for use and able to communicate with your account at "**mySPYPOINT.com**". If an error message shows up, power cycle the camera and go back to TEST mode. If you can't find the solution to the problem, refer to the section "Error Messages" of your user manual and please contact our technical department at 1-888-779-7646 during business hours from Monday to Friday from 8:30 to 17:00 (UTC-05:00) or at the following email address: **tech@spypoint.com**